- 1.27. In this chapter, we introduced a number of general properties of systems. In particular, a system may or may not be
  - (1) Memoryless
  - (2) Time invariant
  - (3) Linear
  - (4) Causal
  - (5) Stable

Determine which of these properties hold and which do not hold for each of the following continuous-time systems. Justify your answers. In each example, y(t) denotes the system output and x(t) is the system input.

(a) 
$$y(t) = x(t-2) + x(2-t)$$

**(b)** 
$$v(t) = [\cos(3t)]x(t)$$

(c) 
$$y(t) = \int_{-\infty}^{2t} x(\tau) d\tau$$

**(b)** 
$$y(t) = [\cos(3t)]x(t)$$
  
**(d)**  $y(t) = \begin{cases} 0, & t < 0 \\ x(t) + x(t-2), & t \ge 0 \end{cases}$ 

(e) 
$$y(t) = \begin{cases} 0, & x(t) < 0 \\ x(t) + x(t-2), & x(t) \ge 0 \end{cases}$$
  
(g)  $y(t) = \frac{dx(t)}{dt}$ 

$$(\mathbf{f}) \ y(t) = x(t/3)$$

(g) 
$$y(t) = \frac{dx(t)}{dt}$$